

Fronti - Wireless Alarm w/LED



80 Ch. (max.)



80 Ch. (max.)

FS250 - 80Ch. Wireless Alarm System

- User also can call-in setup main working mode at anywhere by hand-phone or other phone.
- Eight LED indicators: power on/off, low battery, away armed status, home armed status, fire emergency, medical emergency.
- Four different alarm sounds so user knows type of emergency upon hearing siren.
- Low battery supervision on main console and on each individual sensor.
- Code hopping system uses over one million different code combinations to prevent intruders.
- Can command strategically deployed FS143HS wireless external 110dB siren/strobes.
- Entry and exit delay period adjustable from 0 to 199 sec.
- Alarm sound duration adjustable from 10 to 499 sec.
- Built-in output terminal for connection to any external siren/strobe and NC/NO switch.
- Built-in panic and zone 4 two input terminal NC type for external wire sensors.
- Build-in 2-phone numbers for digital dialer for Central Monitoring Station and 4-phone number for voice dialer.
- Record & report 4 kind of voice messages (total 40 sec.)
- Can combine with FS220GSM auto dialer to report 16 kind of alarm event SMS.
- Hands-free speakerphone, 2-way voice communication.
- Telephone line interruption alarm
- Real Door/Window Open/Closed monitoring warns users of any open access points prior to Arming.
- Call-in setup main console at anywhere by phone
- Can connect to PC by RS232 to report event and control working mode by C.M.S.M system.
- Power Source: DC12V 1A by AC adapter. Working Current: 350mA (Max).
- Stand-by Current: 30mA (Max). Broadcast range: 150 M in a free space.
- Back-up Battery: 1.2Ahr rechargeable.
- Battery Back up time: 24HRS (Min).
- Working temperature range: -10 deg C to 60 deg C.
- Dimensions: 220L x 128W x 56H (mm), Weight: 850g.

FS210 - FEATURES

- Operating modes: Away / Home armed / disarmed and 24-hour panic
- Provides 10-zone total environmental protection from Intrusion, Fire/Smoke/Gas, Sudden Medical Emergencies etc...
- 8 LED indicators: power on/off, low battery, away armed status, home armed status, fire emergency, medical emergency
- Provides 10zone and 80 channel three digital LED for display Zones, wireless sensors number and function total environmental protection
- Built-in Door Chime, Low Battery indication
- 4 different alarm sounds so user knows type of emergency upon hearing siren
- Code hopping system uses over one million different code combinations to prevent intruders
- It can register total 40pcs wireless accessories ID code to the main console.
- Can command strategically deployed FS143HS wireless external 110dB siren/strobes
- Numeric keypad lockout protection to prevent Password hacking.
- Alarm Memory function indicates any previous alarm until manually cleared by user.
- Entry and exit delay period adjustable from 0 to 199 sec
- Alarm sound duration adjustable from 10 to 499 sec
- Built-in output terminal for connection to any external siren/strobe and NC/NO switch
- Built-in panic and zone 4 two input terminal NC type for external wire sensors
- Built-in rechargeable back-up battery and tamper switch and power failure detector function
- Build-in 2*Tel. No. for digital dialer for CMS and 4*Tel.No. for voice dialer. (Total:20sec.)
- Hands-free speakerphone, 2-way voice communication.
- Telephone line interruption alarm, Progress tone decoder and auto busy redial controller
- Real Door/Window Open/Closed monitoring warns users of any open access points prior to Arming.
- Power Source: DC12V 1A by AC adapter.
- Working Current: 350mA (max). Standby: 30mA (max).
- Broadcast range: 150 M in a free space.
- Back-up Battery: 1.2Ahr rechargeable.
- Battery Back up time: 24HRS (min).
- Working temperature: -10 deg C to 60 deg C.
- Dimensions: 220L x 128W x 56H (mm), Weight: 850g.