

ALARM WORKING FUNCTION



FS - 255A



** Design & specification are subject to change without prior notice **

● **Markets & Applications:**

The FS255B PSTN Alarm Console is with digital and voice auto dialer. It can also add option IP/Wi-Fi module to working via internet system on FS330W PC window software operation and setting.

The alarm console has transceiver module that can receive all Fronti wireless accessories working.

It can be combined with Fronti sensors like PIR, Door/Window sensor, AC power detector, temperature sensor, wireless siren, AC power switch andetc. They are completely wireless communication controlling system.

● **Features:**

1. Two partitions of working mode & 70pcs wireless sensors to trigger alarm & 10pcs remote controller.
2. 10 passwords available on PC and Keypad to set working mode.
3. 70pcs sensors can be set to have alarm function of 24H, bypass, delay, door chime and silent.
4. Touch pad for operating alarm working mode, LCD display for working mode, 150logs alarm event.
5. Can connect to PC via USB port on window software read/write setting all programs.
6. It can record 40 seconds and 4 kinds of different emergency voice messages by user.
7. Pre-set to save 2 phone numbers for digital dialer CONTACT ID on alarm calling-out.
8. Pre-set to save 4 phone numbers for playing Voice messages on alarm calling-out.
9. Low battery supervision is on the console and on each individual sensor.
10. Built-in input NC/NO port can connect to wire type sensors, alarm console or panic buttons to call-out to report alarm event.
11. Built-in 2 wires alarms output ports can trigger external siren, and NC/NO relay switch can control the light/CCTV.
12. With 2 channels of temperature sensors which can display INT/EXT -40 to +60°C level data.
13. It can control the FS148S wireless external siren and report event to FS310W wireless keypad LCD.
14. User can send SMS to control the AC power switch ON/OFF.
15. Temperature sensors HI/LO level can control the AC power switch ON/OFF.
16. Timers can control the AC power switch ON/OFF.
17. Call-in to remote to activate hands-free speakerphone, 2-way voice communication.
18. After being connected to emergency call, the called party can listen-in or talk with.
19. Trigger alarm will call-out to contact ID, and then voice dialer will play voice alarm message.
20. Can combine with FS330A APP via IP/Wi-Fi to setting working/program data and receive alarm data.