



VK - 101



VK - 102

| | VK - 101 | VK - 102 |
|---------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------|
| Camera Supported (max.) | 256 | |
| Function | Control full function of the speeddome | |
| Presets (max.) | 128 (8 shots, each shot 16 positions) | |
| Address of Camera/Controller (max.) | 256 | |
| Protocol | Multi-protocol (Pelco-D, Pelco-P, Alec, Samsung, Vido-B01, Neon, HTScam, HD600, Tota, Kalatel, Vcldome, Redapple, Santachi450, Ssantachi650, Vicon | |
| Baud Rate | 1200, 2400, 4800, 9600, 19200 bps | |
| Built-in | 3.5" Colour LCD Display, Joystick | LCD Display, Joystick |
| Communication / Control Port | 2 x RS-485 | |
| Transmitting Distance (max.) | 2400 m | |
| Power Supply & Consumption | DC12V 1A | |
| Operation Temperature & Humidity | -10°C ~ +50°C ; RH 95% (max.) | |
| Storage Temperature | -20°C ~ +60°C ; RH 95% (max.) | |
| Dimension (approximate) | 300(w) x 65(h) x 180(d) mm | |
| Weight (approximate) | 2 kg | |

** Design & specification are subject to change without prior notice **