

FS150H REMOTE CONTROL KEYPAD



The FS150H Remote control keypad gives the end user the power to set the Password, Away Arm, Home Arm, Disarm and trigger an Alarm from anywhere a keypad is deployed.

It can be installed Indoors or Outdoors. An outdoor deployed keypad means the user will never need to worry about a lost or damaged Remote Control preventing them from gaining access to their abode.

The FS150H is work on the "hopping code system" so it has no dip switch's making it installable in seconds and able to accept a rotation of over 1000 000 different system code combinations.

FS150H FEATURES

- Remote control system modes: Away armed / Home armed / Disarmed, 24 hours Panic, Fire Alarm and Medical Help Alarm.
- Built-in Temper Switch.
- Digital keypad lockout for protection from incorrect Password entry (hacking).
- LED to indicate the signal transmission OK and battery condition.

FS150H SPECIFICATIONS

- Power source: DC 9V Alkaline battery 6F22
- Stand-by current: 15uA (Max), Working current: 6mA (Max).
- Broadcast range: 100M in a free space, indoors about 30 M.
- Battery Life: Up to 9 months. (depending on usage, conditions & battery quality).
- Working temperature range: -10 deg C to 60 deg C.
- Dimensions: 110L x 70W x 25H (mm), Weight: 100g.