

FS161H WIRELESS SMOKE DETECTOR WITH SIREN



The FS161H is one of the most reliable optical smoke detectors on the market. It provides very accurate detection in its' monitoring area and is compatible with all traditional Fronti Wireless Security Systems as well.

The wireless design ensures an easy installation and low battery indication ensures constant vigilance.

The FS161H is work on the "hopping code system" so it has no dip switch's making it installable in seconds and able to accept a rotation of over 1000 000 different system code combinations.

FS161H - FEATURES

- Excellent Stability, High Sensitivity.
- Photoelectric chamber.
- Build in a buzzer 85dB.
- Alarm display by LED and buzzer.
- LED indicates the transmitting and battery low condition.

FS161H - SPECIFICATIONS

- Power source: DC 9V Alkaline battery x 1(6F22).
- Stand-by current: 20uA (Max), Working Current: 60mA (buzzer).
- Broadcast range: 100M in a free space, indoors about 30 M.
- Working temperature: -5 deg C to 50 deg C, 95% R.H. (max).
- Battery Life: Up to 9 months. (depending on usage, conditions and battery quality).
- Dimension: Diameter 40mm x H50mm, Weight: 260g