

# LonBon - Voice Intercom



## **LB – 1 T 1-To-1 Voice Intercom**

- Power Supply : DC 6V or 4x1.5V “AA” Battery
- Power Consumption: < 200mA
- Cabling : 2 wires
- Distance(Cable type): 80m(0.2mm<sup>2</sup>), 200m(0.5mm<sup>2</sup>)  
300m(0.75mm<sup>2</sup>),400m(1.0mm<sup>2</sup>)
- Dimension : 85(w) x 70(h) x 220(d) mm

\*\* Package includes power supply x2pcs



*c/w Door / EM.Lock Control*

## **LB – 1 B 1-To-1 Voice Intercom c/w Door Control**

- Power Supply : DC 18V
- Power Consumption: <= 3W
- Relay Output : for connecting E.M.Lock (DC12V)
- Cabling : 2 wires
- Distance(Cable type): 80m(0.2mm<sup>2</sup>), 200m(0.5mm<sup>2</sup>)  
300m(0.75mm<sup>2</sup>),400m(1.0mm<sup>2</sup>)
- Dimension : (Indoor unit) 85(w) x 70(h) x 220(d) mm  
(Outdoor unit) 115(w) x 18(h) x 75(d) mm

\*\* Package includes power supply x1pc

\*\* Design & specification are subject to change without prior notice \*\*